## Device Launch Card Vodafone K4201 USB Stick

Launch

markets:

Price: Volume:





0		

IT, DE, PT (first wave) ES, ZA, UK, CZ, RO, IE, GR, HU, NZ, AL, TR, GH, EG Vodafone exclusive ID Exclusivity: Segments: Young Socials

> For detailed information please refer to VPC

- High speed HSPA+ (21 Mbps) @ very low cost
- QuickStart solution gets the user auto-connected in under 10 seconds
- supporting Plug&Play and Vodafone Mobile Broadband Account Experience(VMBAE) in Windows 8

Vodafone Differentiation & Experience:

- Vodafone exclusive design
- Plug&Play in Windows 8
- Support Vodafone Mobile Broadband Account Experience(VMBAE)
- QuickStart + VMB client for all other platforms
- Vox integration (in MR)
- Dedicated K4201 HVE SKU for VF EG to include hardware network lock

Dimensions:	88.1 x 11.6 x 26.9 mm		
Weight:	23g		
Colors:	White (default)		
Chipset:	HiSilicon Balong 310		
Networks:	GSM / GPRS / EDGE / HSPA+ (21.1 Mbps DL / 5.76Mbps UL)		
Features:	USB 2.0 high speed Breathing LED showing status Rx diversity Vodafone QuickStart Web UI Vodafone hybrid VMB dashboard		
Box content:	Vodafone K4201 Quick Start Guide Product Safety Information		
Key USP:	<ul> <li>Connectivity made simple reducing the support calls</li> <li>Plug&amp;Play in Windows 8</li> <li>Support VMBAE App</li> <li>Quickstart + VMB client for all other platforms</li> <li>Wavingte section (in MD)</li> </ul>		

• Vox integration (in MR)



## Device Facts Sheet Vodafone K4201 USB Stick



Form Factor		Connectivity	
Туре:	USB stick	USB	USB 2.0 high speed
Colours:	White (default)		
Weight:	23g		
Dimensions:	88.1 x 11.6 x 26.9 mm		
Hardware		Software Plat	form
Processor:	HiSilicon Balong 310	User interface:	hybrid VMB client
ROM:	128 <b>M</b>	QuickStart Web UI	
RAM:	32M		Support VMBAE in Win8
Upload:	HSUPA cat 6, 5.6 Mbps		
Download:	HSDPA cat 14, 21.1 Mbps		
LED:	Breathing LED	Messaging	
Antenna:	Advanced antenna support (Type-3i)	Text:	SMS support in QuickStart Web UI
Extermal	N/A		
memory			

## **Network Access**

UMTS:	Dual-band 900, 2100
GSM/GPRS/ EDGE:	Quad-band 850, 900, 1800, 1900
Receive diversity:	900, 2100

